





PRODUCT DATASHEET | EA46.22PRO4
BLUETOOTH BUILT-IN MULTIFUNCTION 2 CHANNEL SWITCH





DESCRIPTION

Recessed switch with astro function. Using mi.puck products, you can easily control, regulate and automate numerous applications in your home through the free mi.puck app, using a cell phone or tablet. The mi.puck app is available for Apple and Android devices.

The recessed mi.puck switches and mi.puck dimmers are small built-in devices that can be easily installed in recessed boxes behind existing switches.

This allows you to continue to control your applications manually via switches as usual, as well as additionally control or program them via the app.



SPECIFICATIONS

Brand:	Hugo muller
Product type:	Switch
Mounting method:	Other
Number of channels:	2
Supply voltage:	230 V
Power supply voltage type:	AC
Frequency supply voltage:	50 - 60 Hz
Autonomy in years:	10
Text guidance in the display:	No
External programming:	Yes
Incl. memory card :	Yes
60-minute program:	Yes
24-hour program:	Yes
Weekly Program:	Yes
Annual Program:	Yes
Vacation Program:	Yes
Impulse program:	No
Cycle Program:	Yes
Astro Program:	Yes
Coincidence Program:	Yes
Operating hour meter:	No
Quartz-controlled:	Yes
Radio-controlled:	No
Radio-controlled (DCF77):	No
GPS:	No
Shortest switching time channel 1:	1 min
Shortest switching time channel 2:	1 min
Number of memory locations:	100
Automatic summer/winter time changeover:	Yes



Manual:	No
External pressure contact input:	No
Preset switching:	No
Potential-free switching contact:	Yes
Degree of protection (IP):	IP20
Width:	44 mm
Height:	41.5 mm
Depth:	20 mm

DOWNLOADS AVAILABLE FROM WEBSITE

Datasheet
Manual