




PRODUCT DATASHEET | IL-DCISET+

EMERGENCY LIGHTING MODULE WITH INVERTER AND BATTERY 3,000MAH





DESCRIPTION

With auto-test inverter and battery backup. Easy plug and play installation. Output: 2.5 watts, 20-60Vdc. This module is already equipped with lithium battery (3,000mAH) for a minimum battery backup of 3 hours. The module comes standard with connection leads and necessary DC cables; this makes this module plug & play. Of course, this connection cable can also be removed so that the module can be wired directly. Supplied with 2 additional male/female DC adapter cords, so that almost any fixture will fit. This module can be connected in three ways: on/off switchable, always ON and always OFF. With LED indicator lamp including test button function. For more information, please refer to the manual. The warranty for the emergency battery is 2 years. The technical lifetime is 4 years, with normal use at temperatures between 0° - 55° C. An annual endurance test is recommended, after 4 years the battery should be replaced preventively.



SPECIFICATIONS

Brand:	Interlight
Product type:	Module
Lamp type:	Other
Power:	2.5 W
Surveillance device:	Other
Circuit type:	Continuous/emergency switching
Nom. voltage :	220 - 240 V
With remote switch connection:	No
Protection class according to IEC 61140:	II
Nom. operating time :	3 - 4 h



ACCESSORIES

Article	Description
IL-DCIBAT	Battery 3,000mAh LiFePO4 for IL-DCISET+

DOWNLOADS AVAILABLE FROM WEBSITE

Certificates
Manual