





PRODUCT DATASHEET | 172413PRO

TERMINAL DI1 W100 16A ASTRO BLUETOOTH 230V 50/60HZ 36MM IP20





DESCRIPTION

Digital time switch, 2 channels: Day and week program. Astro program. DIN-rail mounting. 60 memory locations. 10 year power reserve. Short switching distance 1 minute Programmable without mains connection. Automatic summer time changeover. Ios and Android app available. If the 90 minute shift time is insufficient, you can move the coordinates 7.5 degrees (that's where the sun rises later) 52 degrees N, 2 degrees W (this is normally around 7 /8 degrees).



SPECIFICATIONS

Brand:	Paladin
Product type:	Terminal Astro1-2 AC230 (60) 2TE
Mounting method:	DIN rail
Number of channels:	1
Supply voltage:	230 V
Power supply voltage type:	AC
Frequency supply voltage:	50 - 60 Hz
Autonomy in years:	6
Corridor accuracy per day:	0.5 s
Text guidance in the display:	Yes
60-minute program:	Yes
24-hour program:	Yes
Weekly Program:	Yes
Annual Program:	No
Vacation Program:	Yes
Impulse program:	No
Cycle Program:	No
Astro Program:	Yes
Coincidence Program:	Yes
Operating hour meter:	Yes
Net sync:	No
Quartz-controlled:	Yes
Radio-controlled:	No
Shortest switching time channel 1:	1 min
Number of memory locations:	100
Automatic summer/winter time changeover:	Yes
Manual:	Yes
External pressure contact input:	No
Preset switching:	No



Nom. switching current at 250V AC :	16 A
Potential-free switching contact:	Yes
Degree of protection (IP):	IP20
Width in module units:	2
Width:	35.8 mm
Height:	90 mm
Depth:	63 mm

DOWNLOADS AVAILABLE FROM WEBSITE

Datasheet
Manual